

IR-POCKET THERMOMETER

- LED spot alignment - safer than a laser
- Display hold function
- Lock function for continuous measurement
- Max/min memory function

The IR-Pocket thermometer is a non-contact infrared thermometer that has an easy-to-read, LCD display with low battery indication. Simply aim at the target and press the measure button to display the surface temperature instantly. The IR-Pocket indicates temperature over the range of -9.9 to 199.9 °C with an assured accuracy of $\pm 2\%$ of reading or $\pm 2^\circ\text{C}$, whichever is greater.

The IR-Pocket thermometer features a two-button keypad, pressing the mode button allows the user to access a variety of functions, i.e. max/min, °C/°F, lock and emissivity. The lock function allows for continuous temperature measurement and the emissivity is adjustable so the user can measure a variety of surface types. An auto-power-off facility automatically turns the instrument off after 15 seconds, maximising battery life.

The default emissivity is 0.95 but is adjustable to enable temperature measurement of a variety of surface types.

For some useful infrared thermometer tips, or to download our infrared thermometer guide, please visit our website.



INFRARED

LED spot alignment

The unit incorporates LED spot alignment, which allows the user to precisely target the diameter of the area to be measured. The LED pointer is safer for the eyes than laser pointers. As you move closer or further from the target the LED spot changes diameter indicating the area being measured.



● LED pointer



Specification	IR-Pocket
Range	-9.9 to 199.9 °C
Resolution	0.1 °C/°F
Accuracy	$\pm 2^\circ\text{C}$ or $\pm 2\%$ whichever is greater
Field of view	Target ratio 1:1
Emissivity	0.95 default - adjustable 0.1 to 1
Battery & life	2 x 1.5 volt AAA - 20 hours continuous use
Display	Custom LCD
Dimensions	25 x 52 x 100 mm
Weight	88 grams

Order code	Description	
814-060	IR-Pocket	4099588